



Model Number: C0801S1ULA-22279-S5S5

8-way Single L-band Active LD Series Combiner



The compact 8-way active combiner is part of the LD Combiner Series and is designed to provide affordable L-band splitting in a 1U high, 19" rack mountable chassis.

Front View of Model C0801S1ULA-22279-S5S5

Covering the full range of L-band, 850-2150MHz, this shelf also offers dual redundant power supplies.

Front panel LED's indicate the condition of the dual redundant power supplies.



Rear View of a 16-way Compact LD Series Active Combiner

This particular unit is supplied with 50 ohm SMA RF connectors, but is available in a range of impedances and RF connectors (not N-type RF connectors).





Model Number: C0801S1ULA-22279-S5S5

8-way Single L-band Active LD Series Combiner

RF Engineering
and Custom Build

Technical specifications and operating parameters

PRELIMINARY SPECIFICATIONS

RF Parameters

Capacity	8- way
Frequency Range	850-2150 MHz (L-band)
Gain	0 dB \pm 1.5 dB mean across band
Flatness	\pm 1.0 dB
1dB Compression	+10 dBm output power
IP3	+20 dBm output power
Noise Figure	26 dB
Isolation	25 dB (between any 2 output ports)
Input Return Loss	18 dB typical
Output Return Loss	15 dB typical

System Control

Display	Front Panel LED's for PSU status
---------	----------------------------------

Environmental

Operating temperature	0 to 45°C
Location	Indoor use only
Storage temperature	-20°C to +75°C
Humidity	85% non-condensing

Physical

Input Connectors	SMA
Input Impedance	50 Ω
Output Connectors	SMA
Output Impedance	50 Ω
Dimensions	1U high x 200mm deep x 19" wide
Weight	2 kg
Colour	White 00-E-55 semi-gloss (Front panel)

Power

AC Power	85-264V AC (50/60Hz), Fused 2A
BUC Power	None
PSU	Dual Redundant
Hot-swap PSU	No

Key Features

Housed in a compact 1U high rack

Dual redundant power supplies

Front Panel LED's for PSU status

ETL SYSTEMS LIMITED
Coldwell Radio Station
Madley
Hereford
England HR2 9NE

TELEPHONE
+44 (0)1981 259020

EMAIL
info@etlsystems.com

FACSIMILE
+44 (0)1981 259021

WEB
www.etlsystems.com

