



Model Number: **D0108D2ULA-N5B5**

RF Engineering  
and Custom Build

## 8-way Dual L-band Active Splitter



This splitter shelf contains 2 of ETL's 8-way active equalised splitter modules housed in a 1U shelf. The unit has dual redundant power supplies. LNB bias is not provided. The unit has a dry contact alarm for PSU failure.

Front View of Model D0108D2ULA-N5B5

Front panel LEDs provide a visual status for the power supplies, and monitoring can also be done via a dry contact alarm port on the rear panel.



Rear View of Model D0108D2ULA-N5B5

This particular unit has 50 ohm N-type RF connectors (IN) and 50 ohm BNC RF connectors (OUT), although it is available in a variety of impedances and connector types (model numbers will vary).





# Model Number: D0108D2ULA-N5B5

RF Engineering  
and Custom Build

## 8-way Dual L-band Active Splitter

Technical specifications and operating parameters

### PRELIMINARY SPECIFICATIONS

RF Parameters	
Capacity	8-way Dual
Frequency Range	850 – 2150MHz (L-Band)
Insertion Gain	1 dB ± 1 dB
Flatness	± 1.5 dB
1 dB Compression	0 dBm
Noise Figure	9 dB
Input Return Loss	12 dB typical
Output Return Loss	12 dB typical

System Control	
Display	Front Panel LEDs for PSU & Power Status
Alarms	Dry contact alarm port on rear panel for PSU failure

Environmental	
Operating temperature	0 to 45°C
Location	Indoor use only
Storage temperature	-20°C to +75°C
Humidity	85% non-condensing

Physical	
Connectors	N-type (IN) & BNC (OUT)
Impedance	50Ω
Dimensions	2U high x 350mm deep x 19" wide
Colour	White 00-E-55 semi-gloss (front panel)

Power	
AC Power	85-264V AC (50/60Hz) Fused 2A
LNB Power	None
PSU	Dual redundant
Hot-swap PSU	No

Key Features	
One unit containing 2 x 8-way L-band Splitters	
Dual redundant power supplies	
LEDs for PSU monitoring	
Dry contact alarm port for PSU failure	

ETL SYSTEMS LIMITED  
Coldwell Radio Station  
Madley  
Hereford  
England HR2 9NE

TELEPHONE  
+44 (0)1981 259020  
  
EMAIL  
info@etlsystems.com

FACSIMILE  
+44 (0)1981 259021  
  
WEB  
www.etlsystems.com

