

Falcon Series Frequency Converter Module

L-Band to IF-Band Agile Downconverter

L-Band to IF-Band agile downconverter module with variable gain and slope.

The 1U chassis has the capacity for up to four hot-swap frequency converter modules. These can be all upconverters, all downconverters or a mix of both.

Frequency Converter Module



Frequency Converter Module

Compact form factor allowing multiple modules to be housed in the Genus chassis. Each module occupies 4 slots in the chassis.

Hot Swap & Replaceable

RF Frequency Converter modules

Variable Gain

For balancing input signals.

Redundancy Configurations

Field-replaceable 2+1 or 1+1 redundant configuration

Frequency Conversion

Down conversion from L-Band to IF-Band.

Chassis Options

Local control & monitoring

via HMI high resolution touchscreen

Resilience

from dual redundant hot-swap power supplies & field replaceable CPU & HMI

Compact indoor & outdoor

chassis options, which can be part populated

Secure protocols

with SNMPv3 and HTTPS

Flexible Module Configurations

choose from a mixture of up and down converters with different operating frequencies.

Remote control & monitoring

via RJ45 Ethernet port with SNMP & web browser interface

Field replaceable Internal reference source

and external reference inject port with auto detection



Indoor Chassis



Outdoor Unit



Frequency Downconverter Module - RF Parameters		Redundancy - RF Parameters	
Model Numbers	FN-D-L1F2-24404AA-XXXX	SWF-G1S-CX-111A-xxxx	SWF-G1S-CX-117-xxxx
Size	4 slots wide	4 slots wide	4 slots wide
Redundancy	Standalone module	1+1 (Note: This column denotes specs for 24404 in 1+1 configuration)	2+1 (Note: This column denotes specs for 24404 in 2+1 configuration)
Input Frequency Range	850-3150 MHz in 1 kHz step size		
Output Frequency Range	70 ± 20 MHz / 140 ± 40 MHz		
Mean Conversion Gain	Max. 35 ± 2 dB / Min. 5 ± 2 dB	Max. 34.4 ± 2.2 dB / Min. 4.4 ± 2.2 dB	Max. 34.4 ± 2.3 dB / Min. 4.4 ± 2.3 dB
Gain Step Size	0.1 ± 0.1 dB		
Gain Flatness (50 Ohm)	±0.3 dB	±0.5 dB	±0.6 dB
Input Return Loss (50 Ohm)	Typ. -20 dB / Min. -16 dB	Typ. -15 dB / Min. -10 dB	Typ. -15 dB / Min. -10 dB
Output Return Loss (50 Ohm)	Typ. -20 dB / Min. -16 dB	Typ. -15 dB / Min. -10 dB	Typ. -15 dB / Min. -10 dB
Maximum Operational Input level	- 30 dBm at max gain		
Noise Figure At max. gain	Typ. 8 dB / Max 10 dB	Typ. 8.7 dB / Max 10.7 dB	Typ. 10.7 dB / Max 12.8 dB
OP1dB At max. gain	Typ. +13 dBm / Min. +10 dBm	Typ. +12.3 dBm / Min. +9.3 dBm	Typ. +10.3 dBm / Min. +7.3 dBm
OIP3 At max. gain	Typ. +25 dBm / Min. +22 dBm	Typ. +24.3 dBm / Min. +21.3 dBm	Typ. +22.3 dBm / Min. +19.3 dBm
Internal Reference Stability	± 5 x 10 ⁻⁸ over 0 to 50°C		
Phase Noise (Typical Values)	@10 Hz offset	-70 dBc / Hz	
	@100 Hz offset	-84 dBc / Hz	
	@1 KHz offset	-98 dBc / Hz	
	@10 KHz offset	-104 dBc / Hz	
	@100 KHz offset	-107 dBc / Hz	
	@1 MHz offset	-112 dBc / Hz	
Spurs In-band (@ -5 dBm output)	Carrier related >1MHz offset	< -60 dBc	
	Harmonic	< -50 dBc	
	Non-carrier related	< -75 dBm	
Spurs Out-of-band (@ -5 dBm output)	Carrier related	<-60 dBc	
	Harmonic	< -50 dBc	
	Non-carrier related	<-75 dBm	
LO Breakthrough	< -75 dBm		
Image Rejection	>60 dB Typical		
External Reference Input Frequency	10MHz or 100MHz (auto detection)		
External Reference Input Level	0dBm ± 10dB		
Mute	60 dB		
Number of conversion stages	Dual		
Spectral Inversion	Non-inverting		
Spec version	0.2	1.0	0.1

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.

Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.

Note 3: All specs are for 50 Ohm connectors unless detailed otherwise.