


Piranha Genus Standard LNB DC/10MHz injector

selectable 13/18V 22kHz, up to 500mA.

LNB DC power inserter module (Bias-T) to fit Genus 1U chassis series. Provides selectable 13VDC/18VDC/22kHz tone to LNBs or similar and RF power in monitoring. 10MHz injection onto port1 is switchable on/off when fitted to Genus chassis with 10MHz card fitted. Full control and monitoring of the module is possible locally through the parent chassis HMI (if fitted), or remotely via Ethernet.

DC Inserter Module



DC Inserter Module

Compact form factor allowing multiple modules to be housed in the Genus chassis. Each module occupies 1 slot in the chassis.

Variable voltage

selectable 13/18VDC, and 22 kHz tone to LNBs.

10MHz injection

onto port 1 is switchable on/off (when fitted with 10MHz option).

Hot Swap & replaceable

RF DC Inserter module

Chassis Options

Local control & monitoring

via HMI high resolution touchscreen

Resilience

from dual redundant hot-swap power supplies & field replaceable CPU & HMI

Compact indoor & outdoor

chassis options, which can be part populated

Secure protocols

with SNMPv3 and HTTPS

Flexible Module Configurations

choose from a mixture of DC inserter modules.

Remote control & monitoring

via RJ45 Ethernet port with SNMP & web browser interface

Field replaceable Internal 10MHz reference source

and external reference inject port with auto detection (optional)



Indoor Chassis



Outdoor Unit



PRN BUC DC Power Inserter Module - RF Parameters				
Model Numbers	PRN-G1S-LS2-101			
Size	1 slot wide			
Capacity	Single path			
Frequency Range	850-2500 MHz			
RF Connectors	50Ω SMA	50Ω BNC	75Ω BNC	75Ω F-type
Insertion Loss (dB)	<1.5dB across full band			
Flatness (dB)	Full band	±0.40 dB		
	Any 36MHz	±0.15 dB		
Return Loss (dB)	Typ.	17 dB		
	Min.	14 dB		
Isolation	80 dB min between any two modules			
LNB Voltage	Off. 13V. 18V. 22kHz Tone on/off At port 1. Tolerance ±5% typ.			
LNB Load	Up to 500mA Maximum. Overcurrent protection: Current limited trip and restart.			
10MHz	Switchable on/off to port 1 (see parent chassis for detailed specification)			
Input RF Power	+20dBm. Absolute total maximum			
Module DC Power	12 VDC. Dual redundant 12V bus, module hot swappable			
DC Consumption	12W Full Load. 2W No Load. Max consumption at a steady state.			
RF Power Detect	Range -45dBm to 0dBm total power across band. For indication only			
User Alarms	Via Chassis Ethernet/HMI/Web Interface (upper and lower limits user settable) LNB Current RF Power In			
Remote Control & Monitoring	This module provides monitoring and control via connection with parent chassis. See parent chassis spec for specific details. Voltage/tone/10MHz selection and current monitoring of LNB, and Alarms status monitoring.			
Local Control & Monitoring	Chassis LCD HMI front panel and LNB DC active LED on module face at rear.			
Module Weight	0.2kg			
Module Dimensions	255mm x 45mm x 20mm maximum. PRN-G1x chassis or Genus 1U series mountable.			
Module Finish	Machined Aluminium			
MTBF	>250,000 hrs			
Spec Version	1.0			
Connector Options				
Connector Type	PRN-G1S-LS2-101-xxxx			
SMA 50 Ohm	PRN-G1S-LS2-101-S5S5			
BNC 50 Ohm	PRN-G1S-LS2-101-B5B5			
BNC 75 Ohm	PRN-G1S-LS2-101-B7B7			
F-Type 75 Ohm	PRN-G1S-LS2-101-F7F7			

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.

Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.

Note 3: All specs are for 50 Ohm connectors unless detailed otherwise.