


# GENUS 1U Modular chassis

With Internal 100 MHz reference source.

The GENUS chassis has a modular design which can house any combination of compatible modules within the unit. Supplying operators with a flexible and scalable solution, that reduces spare parts and rack space requirements.


The 1U chassis houses up to 17 RF modules including Amplifiers, BUC/LNB Power Supplies, Frequency Converters, Matrices, RF over Fibre, Redundancy Switches and Test Loop Translators, which can be mixed. Providing a compact 1U system that is smaller in comparison with traditional 19" solutions, which could require 2U, 3U, 4U or more to achieve the same functionality. GENUS provides a cost-efficient solution with field-replaceable components.

The RF modules are field-serviceable and can be inserted whilst the shelf is in service, giving excellent levels of flexibility and resilience. With additional reliability from dual redundant hot-swap power supplies & field serviceable HMI, CPU and optional user replaceable internal 10MHz reference source with external 10MHz input options.



General Specifications		
Capacity	Up to 17 modules <b>Note:</b> actual number dependent on module type fitted	
Dimensions	1U high x 550mm deep x 19" wide	
Weight	<10 kg	
Colour	RAL9003 White (Semi-Matte)	
AC Power	85-264V AC (50/60Hz)	
AC Consumption	275W Max. consumption at steady rate	
PSU	Dual redundant & alarmed, Diode OR, Hot-swap	
RF Modules	Various, hot-swap or field-replaceable dependent upon module type	
Control & Monitoring		
Local Control	HMI, capacitive touchscreen	
Remote Control & Monitoring	Ethernet via RJ45, 10BaseT/100BaseTx ETL TCP/IP protocol SNMPv3 & HTTPS Built-in Web Server	
Environmental		
Operating Temperature	0 to 45°C	
Storage Temperature	-20°C to +75°C Not Powered	
Location/Humidity	Indoor use only — 20 to 90% non-condensing	
Altitude	Operational	10,000 ft AMSL (Above Mean Sea Level)
	Storage	30,000 ft AMSL (Above Mean Sea Level)

A sample of available RF modules						
Amplifier	BUC/LNB Power Supply	Frequency Converter	Matrices	Redundancy Switch	RF Over Fibre	Test Loop Translator (TLT)



Internal 100MHz reference and distribution module for 1U Genus chassis. The integrated 100MHz card has full control and monitoring via the parent chassis HMI or RJ45. The 100MHz reference source is switchable between this on-board ovenised 100MHz oscillator or the customer supplied external reference, connected to slot 17 EXT input module (if fitted). Internal 100 MHz or 10 MHz derived from the external reference can be supplied outside the chassis via a separate card at Slot 16. See separate datasheet for external reference source inject card options.

Internal 100MHz —High Stability Ovenised Oscillator	
Frequency Setting	100±0.003 ppm
Output Type	Sinewave
Output Power (typical)	100 MHz +2 dBm 10 MHz +5 dBm
Harmonic Rejection	2 <sup>nd</sup> >45dBc 3 <sup>rd</sup> >60dBc 4 <sup>th</sup> >60dBc 5 <sup>th</sup> >60dBc
SSB Phase Noise dBc/Hz (typical)	10 Hz <-95 100 Hz <-120 1000 Hz <-130 10 000 Hz <-140 100 000 Hz <-150 1 000 000 Hz <-155
Frequency Stability	Over operating temperature: < $\pm 5 \times 10^{-8}$ Load change(±5%): < $\pm 5 \times 10^{-9}$ Power supply variations(±5%): < $\pm 2 \times 10^{-9}$
Frequency Aging (per year)	$\pm 3 \times 10^{-7}$
Alarms	100MHz source RF power level. Card operational status.
	User settable auto switchover for reference source (Int/Ext)
Hot-Swap	Field replaceable by user

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.

Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.