



RF Components

Wideband Low Noise Amplifier


2-6 GHz

Model Number:
A-LNACX-3626

- 16dB typ. gain and 1.2dB typ. noise figure
- Requires 12V external power

Available with RF connector options:

- 50 Ω SMA



Compact


Housed in rugged compact enclosure

12V

External DC powering

2 - 6 GHz

Operating frequency range. Wide-Band ready



RF Parameters		
A-LNACX-3626-XXXX	S5S5	
Frequency Range	2-6 GHz	
RF Connectors	50Ω SMA	
Gain (dB)	16±3	
Flatness ± (dB)	1.5	
Input Return Loss (dB)	Typ.	13
	Min	7
Output Return Loss (dB)	Typ.	15
	Min	9
Output P1dB GCP** (dBm)	Typ.	22
	Min	20
Output IP3 (dBm)	Typ.	33
Noise Figure (dB)	Typ.	1.2
Isolation (dB)	Typ.	25
**Gain Compression Point		

Broadcast



Marine Oil & Gas



SNG & VSAT



Satellite Teleport





RF Components

Model Number:
A-LNACX-3626
Wideband Low Noise Amplifier


Technical specifications and operating parameters

Environmental		
Operating Temperature		-45°C to +85°C
Storage Temperature		-55°C to +125°C
Location		Indoor use Only
Humidity	Max	85% non-condensing
Altitude	Max	10,000 feet

Max Operating Parameters	
Input RF Power	+5dBm
DC Voltage	12V
DC Current	N/A
DC Consumption	280mA

! Operation beyond these limits may cause instantaneous and permanent damage.

Physical Dimensions in mm (inch) Note: Heat sink required during operation



Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved specification accuracy.

ETL SYSTEMS LIMITED
Coldwell Radio Station
Madley
Hereford
England HR2 9NE

TELEPHONE
+44 (0)1981 259020

EMAIL
info@etlsystems.com

FACSIMILE
+44 (0)1981 259021

WEB
www.etlsystems.com

