



# Falcon Series

## Frequency Converter Module

### C-Band to L-Band Block Downconverter

**Typical applications:**

- Teleports & Earth Stations
- Satellite Operations
- Government & Defence applications
- Telemetry, Tracking & Command
- High Resilience applications

C-Band to L-Band block downconverter module with variable gain and slope.

The 1U chassis has the capacity for up to four hot-swap frequency converter modules. These can be all upconverters, all downconverters or a mix of both.

#### Frequency Converter Module



**Frequency Converter Module**

Compact form factor allowing multiple modules to be housed in the Genus chassis. Each module occupies 4 slots in the chassis.



**Hot Swap & replaceable RF**

Frequency Converter modules



**Redundancy configurations**

Field-replaceable 2+1 or 1+1 redundant configuration



**Variable Gain & Slope**

For balancing input signals.



**Frequency Conversion** Down conversion from C-Band to L-Band.

#### Chassis Options



**Local control & monitoring** via HMI high resolution touchscreen



**Flexible Module Configurations** choose from a mixture of up and down converters with different operating frequencies.



**Resilience** from dual redundant hot-swap power supplies & field replaceable CPU & HMI



**Remote control & monitoring** via RJ45 Ethernet port with SNMP & web browser interface



**Compact indoor & outdoor** chassis options, which can be part populated



**Field replaceable Internal reference source** and external reference inject port with auto detection



**Secure protocols** with SNMPv3 and HTTPS



Indoor Chassis



Outdoor Unit





Frequency Downconverter Module - RF Parameters		Redundancy - RF Parameters	
Model Numbers	FN-D-C1L1-24426AA-XXXX	SWF-G1S-CX-111A-xxxx	SWF-G1S-CX-117-xxxx
Size	4 slots wide	4 slots wide	4 slots wide
Redundancy	Standalone module	1+1 (Note: This column denotes specs for 24426 in 1+1 configuration)	2+1 (Note: This column denotes specs for 24426 in 2+1 configuration)
Input Frequency Range (user selectable)	Mode 1: 3400 – 4400 MHz Mode 2: 3600 – 4600 MHz Mode 3: 3800 – 4800 MHz		
Output Frequency Range	1150–2150 MHz		
Mean Conversion Gain	Max. 35 ± 1.5 dB / Min. 0 ± 1.5 dB	Max. 33.9 ± 2.2 dB / Min. 3.9 ± 2.2 dB	Max. 34 ± 2.5 dB / Min. 4 ± 2.5 dB
Gain steps	0.25 ± 0.15 dB		
Gain Flatness (50 Ohm)	Full L-Band ±1.5 dB Any 40MHz ±0.3 dB	Full L-Band ±1.7 dB	Full L-Band ± 2.0 dB
Slope Compensation	0-6 dB (pivot point at 2150MHz)		
Slope Control Steps	1 dB		
Input Return Loss (50 Ohm)	Typ. -18 dB / Min. -15 dB	Typ. -13 dB / Min. -9 dB	Typ. -13 dB / Min. -9 dB
Output Return Loss (50 Ohm)	Typ. -18 dB / Min. -15 dB	Typ. -13 dB / Min. -10 dB	Typ. -13 dB / Min. -10 dB
Noise Figure At max. gain	Typ. 12 dB / Max 14 dB	Typ. 14.5 dB / Max 16.5 dB	Typ. 15 dB / Max 17 dB
Maximum Operational Input level	-30 dBm At max gain		
OP1dB At max. gain	Typ. +15 dBm / Min. +13 dBm	Typ. +12.5 dBm / Min. +10.5 dBm	Typ. +12 dBm / Min. +10 dBm
OIP3 At max. gain	Typ. +25 dBm / Min. +23 dBm	Typ. +23.0 dBm / Min. +21.0 dBm	Typ. +22.5 dBm / Min. +20.5 dBm
Internal Reference Stability	± 5 x 10 <sup>-8</sup> over 0 to 50°C		
Phase Noise (Typical values )	@10Hz offset	-68 dBc / Hz	
	@100Hz offset	-80 dBc / Hz	
	@1KHz offset	-92 dBc / Hz	
	@10KHz offset	-106 dBc / Hz	
	@100KHz offset	-107 dBc / Hz	
	@1MHz offset	-115 dBc / Hz	
Spurs In-band	Non-carrier related	< -75 dBm (At -5dBm Output. Non-Harmonic)	
	Carrier Related (>1MHz Offset)	< -60 dBc (At -5dBm Output. Non-Harmonic)	
Spurs Out-of-band	Carrier related	< -60 dBc (At -5dBm Output)	
	Non-carrier related	< -75 dBm (At -5dBm Output)	
LO Breakthrough	< -75 dBm		
Image Rejection	>60 dB		
Conversion stages	Dual		
External Reference Input Frequency	10MHz or 100MHz (auto detection)		
External Ref Input Leve	0dBm ± 10dB		
IF Monitor Port	Yes		
Mute	60 dB		
Spectral Inversion	Non-inverting		
Spec version	0.1	1.0	0.1

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.

Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.

Note 3: All specs are for 50 Ohm connectors unless detailed otherwise.

ETL SYSTEMS LIMITED  
Coldwell Radio Station  
Madley  
Hereford  
England HR2 9NE

TELEPHONE  
+44 (0)1981 259020

WEB  
www.etlsystems.com

EMAIL  
info@etlsystems.com

