

Model Number: C1601S2ULA-22439

16-way Single L-band Active Combiner

with 0-20dB variable gain

Typical applications:

- Satellite operators, VSAT, teleports, and broadcasters
- High resilience RF distribution, and optimum satellite signal quality



















Model Number: C1601S2ULA-22439

16-way Single L-band Active Combiner with 0-20dB variable gain

Technical specifications and operating parameters

RF Parameters						
Capacity		16-way				
Frequency Range		850-2150 MHz (L-band)				
RF Connectors		50Ω SMA	50Ω N-type	50Ω BNC	75Ω BNC	75Ω F-type
Flatness	850-2150MHz	±1.0 dB	±1.0 dB	±1.0 dB	±1.5 dB	±1.5 dB
	Any 36MHz	±0.25 dB	±0.25 dB	±0.25 dB	±0.3 dB	±0.3 dB
Input Return Loss	Typical	18 dB	18 dB	16 dB	12 dB	10 dB
	Minimum	12 dB	12 dB	10 dB	8 dB	8 dB
Output Return Loss	Typical	15 dB	15 dB	14 dB	10 dB	10 dB
	Minimum	11 dB	11 dB	10 dB	8 dB	8 dB
Gain		0-20 dB ±1.0 dB, Mean across band				
Isolation (Min. between any two output ports)	Typical	28 dB	28 dB	28 dB	28 dB	28 dB
	Minimum	24 dB	24 dB	24 dB	24 dB	24 dB
Noise Figure		24 dB typical at maximum gain 28 dB typical at minimum gain				
Input RF Power		20 dBm Absolute maximum			ximum	
Output 1dB GCP (@1.5GHz)		+16 dBm typical at maximum gain +8 dBm typical at minimum gain				

Environmental		
Operating temperature	0 to 50°C	
Location	Indoor use only	
Storage temperature	-20°C to +75°C	
Humidity	85% non-condensing	
Altitude	10,000 feet AMSL	

Power				
PSU Power	85-264Vac 50-60Hz	Fused 2A		
AC Consumption	<20W	Max. consumption at steady state		
LNB Power	None			
PSU	Dual redundant with dual IEC inlets	Diode OR. Not hot swap.		

System Control		
Remote Control	Via RJ45 Ethernet port 10/100 Base T. TCP/ IP, SNMP & Web browser interface	
Alarms	Dry contact (D-type) & Ethernet (RJ45) for PSU status	
Display	Front panel tri colour LED for combiner & PSU status	

Physical		
Dimensions	2U high x 350mm deep x 19" wide	
Weight	8 kg	
Colour	White 00-E-55 semi-gloss	

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.

Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.









