

Piranha Genus Standard LNB DC injector

selectable 13/18V 22kHz, up to 500mA.

LNB DC power inserter module (Bias-T) to fit Genus 1U chassis series. Provides selectable 13VDC/18VDC/22kHz tone to LNBs or similar and RF power in monitoring. Full control and monitoring of the module is possible locally through the parent chassis HMI (if fitted), or remotely via Ethernet.

DC Inserter Module



DC Inserter Module

Compact form factor allowing multiple modules to be housed in the Genus chassis. Each module occupies 1 slot in the chassis.

Variable voltage

selectable 13/18VDC, and 22 kHz tone to LNBs.

Hot Swap & replaceable

RF DC Inserter module

Chassis Options

Local control & monitoring

via HMI high resolution touchscreen

Resilience

from dual redundant hot-swap power supplies & field replaceable CPU & HMI

Compact indoor & outdoor

chassis options, which can be part populated

Secure protocols

with SNMPv3 and HTTPS

Flexible Module Configurations

choose from a mixture of DC inserter modules.

Remote control & monitoring

via RJ45 Ethernet port with SNMP & web browser interface

Field replaceable Internal 10MHz reference source

and external reference inject port with auto detection (optional)



Indoor Chassis



Outdoor Unit

PRN BUC DC Power Inserter Module - RF Parameters					
Model Numbers		PRN-G1S-LS2-102			
Size		1 slot wide			
Capacity		Single path			
Frequency Range		850-2450 MHz			
RF Connectors		50Ω SMA	50Ω BNC	75Ω BNC	75Ω F-type
Insertion Loss (dB)		<1.5dB across full band			
Flatness (dB)	Full band	±0.40 dB			
	Any 36MHz	±0.15 dB			
Return Loss (dB)	Typ.	17 dB			
	Min.	14 dB			
Isolation		80 dB min between any two modules			
LNB Voltage		Off. 13V. 18V. 22kHz Tone on/off At port 1. Tolerance ±5% typ.			
LNB Load		Up to 500mA Maximum. Overcurrent protection: Current limited trip and restart.			
Input RF Power		+15dBm. Absolute total maximum			
Module DC Power		12 VDC. Dual redundant 12V bus, module hot swappable			
DC Consumption		12W Full Load. 2W No Load. Max consumption at a steady state.			
RF Power Detect		Range -50dBm to -10dBm total power across band. For indication only			
User Alarms		Via Chassis Ethernet/HMI/Web Interface (upper and lower limits user settable) LNB Current RF Power In			
Module Weight		0.18kg			
Module Dimensions		175mm x 45mm x 20mm maximum. PRN-G1x chassis or Genus 1U series mountable.			
Module Finish		Machined Aluminium			
MTBF		TBC			
Spec Version		1.0			

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.
Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.
Note 3: All specs are for 50 Ohm connectors unless detailed otherwise.