

CST-BAB-SW-1006

2-way Broadband Coaxial Switch

DC - 3 GHz

- Low insertion loss across the band
- High power handling
- This unit is available in 50 Ohm N-type connectors



Image for reference only, connectors in image are SMA.

General Specification	
Model Number	CST-BAB-SW-1006
RF Connectors	50 Ohm N-type
Power	1500W CW
Isolation	More than 70dB DC to 200 MHz More than 60dB 200 to 1000MHz More than 55dB 1000 to 2000 MHz More than 50dB 2000 to 3000MHz
Insertion Loss	Less than 0.05dB DC to 500 MHz Less than 0.1dB 500 to 1000MHz Less than 0.15dB 1000 to 2000 MHz Less than 0.2dB 2000 to 3000MHz
Weight	15.2 oz (440g)
Size	2.8x1.8x3.7 inches (71x57x42 mm)

Note 1: The specification is subject to regular reviews and will be updated from time to time as part of our continuing product development and improved spec accuracy.

Note 2: Operation beyond the quoted limits stated above may cause instantaneous and permanent damage.















V 1.2 E&OE www.etlsystems.com